We Deliver the Power™

Lex Products Corporation
15 Progress Drive
Shelton, CT 06484
203.363.3738
203.363.3742 Fax

Lex West
11847 Sheldon Street
Sun Valley, CA 91352
818.768.4474
818.768.4040 Fax

www.lexproducts.com
info@lexproducts.com
800.643.4460

PowerPLUS™
Installed Distribution Boxes

Recessed Mount Outlet Boxes

In-Wall Mounted Enclosure

Features & Benefits

- ***Rugged construction results in a dependable product with a long service life***
- ***Cover plate is sized to mask the wall cutout***
- ***A variety of common connectors are offered to meet specific applications***

c UL US LISTED

Catalog Number:

See reverse for catalog numbers and ordering information.

Description:

20 Amp, single phase, 2 pole, 3 wire in-wall mounted receptacle box with 20 Amp Stage pin, 20 Amp Locking (L5-20) or 20 Amp Edison (5-20) connectors. Outputs can be either receptacles or on 18" pigtails. Input connections are made to a molded barrier terminal strip. The outlet box is mounted in a recessed opening in a wall.

Typical Application:

Recessed mount outlet boxes are often used backstage, or in studios as a power source for floor level lighting. Other locations may include catwalks, and lighting control booths.

Markets Served:

Theatrical, Motion Picture and Television Production, Convention Centers

Specifications

Rating	20 Amp, 1 Phase, 2 Pole, 3 Wire, 120 VAC
Environmental Rating	NEMA Type 1 Indoor
Input	Molded barrier terminal strip
Output	20 Amp Stage Pin, 20 Amp Locking (L5-20) or 20 Amp Edison. Flush or 18" 12/3 SO pigtails.
Enclosure	16 gauge steel back box
Finish	Matte black powder coat

©2011 Lex Products Corp. All Rights Reserved

PowerPLUS™
Installed Distribution Boxes

Recessed Mount Outlet Boxes

In-Wall Mounted Enclosure

Ordering Information:

Catalog No.	Description	Enclosure Size (L x W x D)
20 Amp Stage Pin		
PPR-2-AA	Flush Box with Two (2) 20 Amp Stage Pin Receptacles	6” x 6” x 4”
PPR-3-AA	Flush Box with Three (3) 20 Amp Stage Pin Receptacles	8” x 6” x 4”
PPR-4-AA	Flush Box with Four (4) 20 Amp Stage Pin Receptacles	10” x 6” x 4”
PPR-6-AA	Flush Box with Six (6) 20 Amp Stage Pin Receptacles	12” x 6” x 4”
PPR-2-AC	Flush Box with Two (2) 20 Amp Stage Pin Pigtails	6” x 6” x 4”
PPR-3-AC	Flush Box with Three (3) 20 Amp Stage Pin Pigtails	8” x 6” x 4”
PPR-4-AC	Flush Box with Four (4) 20 Amp Stage Pin Pigtails	10” x 6” x 4”
PPR-6-AC	Flush Box with Six (6) 20 Amp Stage Pin Pigtails	12” x 6” x 4”
20 Amp Locking (L5-20)		
PPR-2-GA	Flush Box with Two (2) 20 Amp Locking Receptacles	6” x 6” x 4”
PPR-3-GA	Flush Box with Three (3) 20 Amp Locking Receptacles	8” x 6” x 4”
PPR-4-GA	Flush Box with Four (4) 20 Amp Locking Receptacles	10” x 6” x 4”
PPR-6-GA	Flush Box with Six (6) 20 Amp Locking Receptacles	12” x 6” x 4”
PPR-2-GC	Flush Box with Two (2) 20 Amp Locking Pigtails	6” x 6” x 4”
PPR-3-GC	Flush Box with Three (3) 20 Amp Locking Pigtails	8” x 6” x 4”
PPR-4-GC	Flush Box with four (4) 20 Amp Locking Pigtails	10” x 6” x 4”
PPR-6-GC	Flush Box with Six (6) 20 Amp Locking Pigtails	12” x 6” x 4”
20 Amp Edison (5-20)		
PPR-2-DA	Flush Box with Two (2) 20 Amp Edison Receptacles	6” x 6” x 4”
PPR-3-DA	Flush Box with Three (3) 20 Amp Edison Receptacles	8” x 6” x 4”
PPR-4-DA	Flush Box with Four (4) 20 Amp Edison Receptacles	10” x 6” x 4”
PPR-6-DA	Flush Box with Six (6) 20 Amp Edison Receptacles	12” x 6” x 4”
PPR-2-DC	Flush Box with Two (2) 20 Amp Edison Pigtails	6” x 6” x 4”
PPR-3-DC	Flush Box with Three (3) 20 Amp Edison Pigtails	8” x 6” x 4”
PPR-4-DC	Flush Box with Four (4) 20 Amp Edison Pigtails	10” x 6” x 4”
PPR-6-DC	Flush Box with Six (6) 20 Amp Edison Pigtails	12” x 6” x 4”

©2011 Lex Products Corp. All Rights Reserved