



We Deliver the Power™

Lex Products Corporation  
15 Progress Drive  
Shelton, CT 06484  
203.363.3738  
203.363.3742 Fax

Lex West  
11847 Sheldon Street  
Sun Valley, CA 91352  
818.768.4474  
818.768.4040 Fax

[www.lexproducts.com](http://www.lexproducts.com)  
[info@lexproducts.com](mailto:info@lexproducts.com)  
800.643.4460

## 50 Amp Pagoda Jr. to Edisons, Feed Thru

**PowerHOUSE™**  
Portable Distribution Boxes



**Catalog Number:**  
**DB-50NQ-BBB-S3**

### Description:

50 Amp, Single Phase, 3 Pole, 4 Wire, 120/240 VAC, Pagoda Jr. Enclosure, (1) 50 Amp California-style locking inlet to (6) NEMA 5-20, 20 Amp, 120 VAC duplex receptacles, feed thru, NEMA 3R Weather Resistant.

### Typical Application:

This box provides a large number of 20 Amp Edison receptacles for use in industrial maintenance and temporary structures to power lights, fans, pumps, tools and computers.

### Markets Served:

Industrial, Emergency/Disaster Relief

## Features & Benefits

- *Heavy-duty molded rubber enclosure is fully insulated and resistant to shock, impact and corrosion*
- *Breakers are mounted under hinged lid for enhanced safety*
- *Stackable and compact for easy storage and convenient portability*
- *Elevated base keeps receptacles above ground level*

## Specifications

<b>Rating</b>	50 Amp, Single Phase (H,H,N,G), 3 Pole, 4 Wire, 120/240 VAC
<b>Environmental Rating</b>	NEMA 3R Weather Resistant
<b>Input</b>	(1) 50 Amp, Single Phase, 3 Pole, 4 Wire, 120/240 VAC, California-style locking inlet
<b>Output</b>	(6) NEMA 5-20, 20 Amp, Single Phase, 2 Pole, 3 Wire, 120 VAC duplex receptacles
<b>Feed Thru</b>	(1) 50 Amp, Single Phase, 3 Pole, 4 Wire, 120/240 VAC, California-style locking receptacle
<b>Overcurrent Protection</b>	(6) 20 Amp, Single Pole branch-rated circuit breakers
<b>Dimensions</b>	8.5"L x 8.5"W x 11"H
<b>Approximate Weight</b>	32 lbs.